



DC-DC Step Down Converters

Model
SDC-12
12 Amps

Design Features

- Advanced switchmode design
- Mount in almost any location
- Compact and light weight
- Reverse polarity protection
- High efficiency
- Cycle by cycle current limiting circuit
- Over voltage protection
- Short circuit protection

Applications

- Earth moving equipment
- Heavy trucks
- Buses
- Marine vehicles
- CB radios
- 12 Volt lighting systems
- AM / FM sound systems

2 YEAR LIMITED WARRANTY



MODEL NO. SDC-12

CAUTION! THERE IS NO ISOLATION BETWEEN THE INPUT AND THE OUTPUT INPUT AND OUTPUT HAVE A COMMON NEGATIVE

VOLTAGE	INPUT TO OUTPUT ISOLATION	Not isolated. Input and output connections have a common negative
	INPUT VOLTAGE	20 to 32 VDC
	OUTPUT VOLTAGE	13.6 VDC \pm 0.1 V
	OUTPUT VOLTAGE REGULATION	3%
	INPUT CURRENT AT NO LOAD	< 5 mA
OUTPUT CURRENT	CONTINUOUS	12 A
	CURRENT LIMIT *	12.5 A
ENVIRONMENT	OUTPUT RIPPLE AND NOISE	Less than 50 mV RMS
	EFFICIENCY	92%
	OPERATING AMBIENT TEMPERATURE	- 20° to + 30° C
PROTECTIONS	HUMIDITY	Max. 95%, non condensing
	OVERLOAD	By current limiting
	REVERSE POLARITY	Internal 10A fuse / external fuse will blow
	OVER VOLTAGE	Varistor (also protects against load dump)
SAFETY AND EMC STANDARDS	INPUT SIDE FUSE	10A (inside the unit)
	EMISSION	EN50081-1
	IMMUNITY	EN50082-1
GENERAL	AUTOMOTIVE DIRECTIVE	95 / 45 / EC
	INPUT / OUTPUT CONNECTIONS	Terminal Block - 6.3 mm male flat tab, quick connect
	DIMENSIONS, MM (W x D x H)	88 x 98 x 49
	DIMENSIONS, INCHES (W x D x H)	3.5 x 3.9 x 1.9
	WEIGHT, KG	0.27
	WEIGHT, LB	0.6

Specifications are subject to change without notice

*NOTE: In current limit condition, the output voltage will drop if the current draw increases beyond the current limit value of 12.5 A